

WC12000 PEPAdvantage™ Cellular Installation Kit

The following items are *supplied to the installer*:

- Broadband router
- Router power connector
- NEMA 4X Gray enclosure
- 18"x12" Plastic EV sign
- 3/16" x 14¼" x 9" Mounting flange
- ¾" Conduit compression connector
- (2) Torx tamper resistant screws (M4X.7X22mm)
- T-20 Tamper resistant Torx bit
- (4) Hex screws (M4X0.7X40mm)
- (4) Fender washers (M4X12mm OD)
- (2) ¼"-20 x 2½" SS button head screw
- (2) ¼"-20 Nylon insert hex flange locknuts
- (4) ¼"-20 x ¾" Zinc washers
- (4) #8 x ¾" Sheet metal screws
- (2) 3M #558 Wire connectors

The following items are *supplied by the installer*:

- ¾" PVC conduit
- 10'x3¼"x1½" U-channel green baked enamel sign post
- General cable #E1032S or equivalent: Two-wire, 18 gauge, stranded, with PVC jacket, and black & red conductors, unshielded (length as req'd.)
- (2) 18 gauge wire nuts
- CAT5 Ethernet cable and RJ45 connectors
- Plastic zip ties

